

User Manual

Wi-Fi Smart Plug



Use your phone to scan the QR code below or search "Smart life" in application market to download and install the App

1

Catalogue

1. Download QR code from App-----1
2. Instructions in English-----3-5
3. Instructions in German-----6-8
4. Instructions in French-----9-11
5. Instructions in Italian-----12-14
6. Instructions in Spanish-----15-17
7. Schematic diagram of operation interface-----18-21
8. Thank you-----22

English

Product parameters

Features : Mobile phone control, switch, countdown, timing.
Power: 16A
Rated power: 0-3840W
Input voltage : 100V-240V
Output voltage : 100V-240V
Communication : WiFi (2.4G) IEEE802.11b/g/n + Bluetooth
Certification : CE/RoHS
Overload protection : Stand by
Application support : ISO 8.0 or Android 4.2 and higher
Shell material : PC plastic
Operating temperature : -10℃ - 50℃
Product size (mm) : 121*115*56mm
Package size (mm) : 224*127*61mm
N.W:305g
G.W:380g

Instructions

1. Download Smart Life app / Tuya smart app on mobile phone;
2. Register an account and log in;
3. The product and mobile phone are covered by 2.4G network, and the mobile phone is connected to 2.4G WiFi network;
4. When the product is powered on, press and hold the product button for 3-5 seconds, and the indicator light flashes;
5. Open the app and add products (see page 18-21 for two addition methods)

2

Connect with mobile phone(Auto Scan)

- 4A1. Turn on Bluetooth and connect 2.4G WiFi;
- 4A2. Open app and select add product;
- 4A3. Select auto add and press the prompt to enter the next step;
- 4A4. Wait for registration connection;
- 4A5. Added successfully.

Connect with mobile phone(Add Manually)

- 4B1. Turn on Bluetooth and connect 2.4G WiFi;
- 4B2. Open app and select add product;
- 4B3. Select electrical type and plug;
- 4B4. Select the same 2.4G WiFi network as the mobile phone, and enter the WiFi password;
- 4B5. Press the prompt to confirm the next step and wait for the registration connection;
- 4B6. Added successfully.

Support 3rd Party Control

1. Type the edit menu of the user panel
2. Select the third-party application to be operated
3. Follow the instructions in the tutorial to connect and use

Warm Tips

- Please check whether the device is connected with power and your phone is connected with WiFi.
- Check routers: If the router is dual-band router, please select a 2.4GHz network to add device, you also need to open the router broadcasting function.
- set up the wireless router: set encryption method as WPA2-PSK authorization type as AES, or set both as auto. The Wireless mode cannot be only 5GHz. Please name router WiFi in English order to stay strong WiFi signal, please keep device and router within a certain distance.
- Check whether connected devices have reached the Maximum number router connection, if so, please try to turn off the WiFi connection of some devices.
- Make sure router wireless MAC filtering function is enabled.
- Remove the device from the filter list and make sure that router is not prohibiting device from connection.
- Make sure the entered password is correct when adding a new device.
- APP for more operations, please refer to the corresponding application tutorial.


3

Add Manually

① Manual addition - socket




② Enter the 2.4GHz WiFi account password



Auto Scan

① Turn on Bluetooth and select auto discovery




② Enter the 2.4GHz WiFi account password



Auto Scan

③ Follow the prompts to go to the next step




④ Added successfully



Add Manually

③ Follow the prompts to go to the next step



④ Added successfully



Thank You

Remark

- 1) The pictures used in this manual are iOS app interface, Android version is a bit different.
- 2) Product and software update periodically, the number and app interface in this manual are only for example. No extra notification on further changes.